


DIM IN
 2.03 .08
 4.06 .16
 9.39 .37
 22.09 .87
 22.60 .89
 32.51 1.28
 50.80 2.00

9023



NOTES:

- 1) COPPER ALLOY CONTACTS
- 2) NUMBER OF POLES 1
NUMBER OF THROWS 1
- 3) SEALING-NONE
- ④ 4) ALL STEEL PARTS PLATED

5) RATING:

	RESISTIVE	INDUCTIVE
12V	15 AMPS	10 AMPS
24V	8 AMPS	5 AMPS

LIFE @ RATED CURRENT
 MAKE & BREAK / 12V-100,000 MIN.
 24V-50,000 MIN.

METRIC

Confidential Property of Cole Hersee

DO NOT SCALE

LET.	WAS	DATE	BY	LET	WAS	DATE	BY	MATERIAL	DRAWN	CHECKED	APPROVED	SCALE	DATE DRAWN
								W.R.	AF			1:1	2-28-46
				T	NOTE 54169	5-11-01	SA	FINISH					DATE BLUEPRINT
				S	ECN 02321	6-25-02	M.L.						
				R	CAD 125234	11/1/92	J.P.	TOLERANCES					
				Q	REORAM N	5/16/87	J.P.	DECIMAL ±					
								METRIC ±					

Cole Hersee Co.
3400 COLE DRIVE, FORT WORTH, TEXAS 76107

STARTER SWITCH

9023